

DuraFon 4X Line Dedication Set Up

To set up DuraFon 4X system for dedicated line operations, the following steps are required as the factory default settings are different.

Before we start, we have to register the handset(s) to the system properly by following the steps of Handset Registration in page 34 of the User Manual.

These steps can only be performed by the handsets of IDs 10 or 11.

Turn on the base station unit and wait for 20 seconds to start up. Then turn on the handsets of IDs 10 or 11.

<u>Steps</u>	<u>Buttons to press</u>	<u>Displayed screens</u>
Step 1.	Menu	Main menu
Step 2.	9 (Select Admin)	Admin
Step 3.	1 (Select Auto Attendant)	Searching for base.... Attenda
Step 4.	4 (Select AA On/Off)	Select Line
Step 5.	Up/Down arrow keys	1 (line # that you work on currently) On Off (AA turned on or off)
Step 6.	Off (to turn off AA)	AA turned off Dedicate Line?
Step 7.	Yes (to enable line dedication)	Please enter Ext. #:
Step 8.	10 (Handset ID that dedicated to this line, it can be any ID of the system)	Done

Repeat from step 4 to step 8 to work on the next line(s) (i.e. line 2, line 3 and line 4) until all the required lines are done.